

## Fuse table

### Blaze

Maximum loading of automatic of circuit breakers

		Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current
		Installation Ø	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	1,5 mm	2,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	I <sub>max</sub> time
<b>Blaze</b> , 1 luminaire	phase-cut	LCBI 15W 350mA BASIC phase-cut SR	50	65	80	100	50	65	80	100	1,7 A 40µ
<b>Blaze</b> , 2 luminaires	phase-cut	LCBI 25W 700mA BASIC phase-cut SR	30	39	48	60	30	39	48	60	2,5 A 60µ
<b>Blaze</b> , 1-2 luminaires	DALI	LCA 25W 350-1050mA one4all SC PRE	31	43	53	66	19	26	32	40	26 A 151µ

Maximum loading of automatic of circuit breakers

		Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current
		Installation Ø	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm	4 mm <sup>2</sup>	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	4 mm <sup>2</sup>	I <sub>max</sub> time
<b>Blaze</b> , 3 luminaires	DALI	LCA 45W 500-1400mA one4all SC PRE	23	31	38	48	14	19	23	29	23 A 200µ