

Fuse table

Phenix G2

Maximum loading of automatic of circuit breakers

	Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20
Art.no.	Installation Ø	1,5 mm ²	1,5 mm ²	2,5 mm ²	2,5 mm ²	1,5 mm ²	1,5 mm ²	2,5 mm ²	2,5 mm ²
4232, On/Off	LC 75W 100-400mA flexC Ip EXC	16	21	26	35	10	13	16	21
4232, DALI	LCA 75W 100-400mA one4all Ip PRE	21	28	35	45	13	17	21	27
4233; 4234; 4235 On/Off	LC 75W 350-1050mA flexC Ip EXC	16	21	26	35	10	13	16	21
4230; 4231 DALI	LCA 50W 100-400mA one4all Ip PRE	21	28	36	45	13	17	22	27
4231, On/Off	LC 50W 100-400mA flexC Ip EXC	16	21	26	35	10	13	16	21
4233, DALI	LCA 35W 150-700mA one4all Ip PRE	30	38	46	58	18	23	28	35
4230, On/Off	LC 50W 100-400mA flexC Ip EXC	16	21	26	35	10	13	16	21
	Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20
Art.no.	Installation Ø	1,5 mm ²	1,5 mm ²	2,5 mm ²	4 mm ²	1,5 mm ²	1,5 mm ²	2,5 mm ²	4 mm ²
4234; 4235 DALI	LCA 75W 350-1050mA one4all Ip PRE	15	20	23	30	9	12	14	18