

## Fuse table

### Worker 400

Maximum loading of automatic of circuit breakers

#### DALI

LCAI 35W 350mA–900mA ECO C  
Leakage current (PE) < 0.35 mA

Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current
Installation Ø	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	4 mm <sup>2</sup>	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	4 mm <sup>2</sup>	$I_{max}$ time
LCAI 35W 350mA-900mA ECO C	26	36	42	50	13	18	21	25	5 A 20μ

Maximum loading of automatic of circuit breakers

#### ON/OFF

LCAI 35W 350mA–900mA TOP C  
Leakage current (PE) < 0.5 mA

Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current
Installation Ø	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	$I_{max}$ time
LCAI 35W 350mA-900mA TOP C	35	45	55	70	35	45	55	70	9 A 40μ

## Fuse table

### Worker 600

Maximum loading of automatic of circuit breakers

#### DALI

LCAI 100W 900mA–1750mA ECO C  
Leakage current (PE): 0.47 mA

Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current
Installation Ø	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	4 mm <sup>2</sup>	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	4 mm <sup>2</sup>	$I_{max}$ time
LCAI 100W 900mA–1750mA ECO C	10	18	22	26	6	9	11	13	43,5 A 210µ

Maximum loading of automatic of circuit breakers

#### ON/OFF

LCAI 100W 900mA–1750mA TOP C  
Leakage current (PE) < 0.5 mA

Automatic circuit breaker type	C10	C13	C16	C20	B10	B13	B16	B20	Inrush current
Installation Ø	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	1,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	2,5 mm <sup>2</sup>	$I_{max}$ time
LCAI 100W 900mA–1750mA TOP C	12	18	28	30	6	9	14	15	50 A 200µ