

## Fuse table

### Pepper 2700 DALI

<b>Automatic circuit breaker type:</b>	C10	C13	C16	C20		B10	B13	B16	B20	B25	Inrush current
<b>Driver:</b> OT 60/170-240/1A0 4DIMLT2 E											$I_{max}$ time
<b>Number of drivers/fuse:</b>						7	12	14	16	20	53 A 200 $\mu$ *

\* Input voltage 230V, Time measured at 50% Ipeak

### Pepper 4300, 6000, 8000 On/Off

<b>Automatic circuit breaker type:</b>	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
<b>Driver:</b> Philips Xi LP 70W 0.2-0.7A S1 230V C150 sXt Philips Xi LP 110W 0.3-1.0A S1 230V C150 sXt											$I_{max}$ time
<b>Number of drivers/fuse:</b>	11	15	19	23	29	7	9	11	14	17	42 A 280 $\mu$ *

\* Input voltage 230V, Time measured at 50% Ipeak

>>>

## Pepper 4300, 6000, 8000 DALI

Inrush current

Automatic circuit breaker type:	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	$I_{max}$	time
<b>Driver:</b> Philips Xi FP 75W 0.2-0.7A SNLDAE 230V C133 sXt Philips Xi FP 110W 0.3-1.0A SNLDAE 230V C133 sXt											43 A 47 A	260 $\mu$ * 250 $\mu$ *
<b>Number of drivers/fuse:</b>	10	14	17	21	26	6	8	10	13	16		

\* Input voltage 230V, Time measured at 50% Ipeak

## Pepper 10000 On/Off (not available with DALI)

Automatic circuit breaker type:	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current	
<b>Driver:</b> Philips Xi LP 165W 0.5-1.5A S1 230V C170 sXt											$I_{max}$	time
<b>Number of drivers/fuse:</b>	7	9	12	15	18	4	6	7	9	11	41 A	440 $\mu$ *

\* Input voltage 230V, Time measured at 50% Ipeak