

Fuse table

Time Direct / Indirect 1140, 1420

Maximum loading of automatic of circuit breakers

	Automatic circuit breaker type:	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Driver:	Xitanium 36W 0.3-1A 54V TD 230V											I_{max} time
	Number of drivers/fuse: There are 2 drivers / DALI address in each luminaire	37	49	61	75	94	23	29	36	45	56	26 A 140 μ^*

* Input voltage 230V, Time measured at 50% Ipeak

Time Direct / Indirect 1700, 2260, 2820

Maximum loading of automatic of circuit breakers

	Automatic circuit breaker type:	C10	C13	C16	C20	C25	B10	B13	B16	B20	B25	Inrush current
Driver:	Xitanium 75W 0.7-2A 54V TD 230V											I_{max} time
	Number of drivers/fuse: There are 2 drivers / DALI address in each luminaire	25	32	41	50	62	15	19	24	30	37	24,9 A 215 μ^*

* Input voltage 230V, Time measured at 50% Ipeak